









# TIMOTHY OULTON

## ASSEMBLY INSTRUCTION

VOID WALLART

### PARTS ENCLOSED

ITEMS	DIAGRAM	DESCRIPTION	QTY.
(A)		<b>Junction Box</b> (Not included) 100LB.MIN.FIXTURE RATED	1
(B)		<b>Mounting Screws</b> (Not included)	10
(C1)		<b>Wire Nut</b>	3
(C2)		<b>Terminal Block</b>	1
(D)		<b>Wall Mounting Plate</b>	1
(E)		<b>Body</b>	1

### IMPORTANT SAFETY INSTRUCTIONS:

1. Use an authorized and certified electrician for consultation and installation.
2. This fixture has been rated for 24watt maximum LED light strip.
3. To avoid the risk of fire, do not exceed the recommended wattage.
4. The wall must have at least the capacity of 5 times the weight of the wall lamp.  
For this light at least a wall capacity of 290.kg (639.34lbs) is required.
5. The manufacturer and distributor accept no liability for incorrect installation.
6. For indoor use only.
7. Keep away from children.

### WARNINGS:

1. Turn-off electricity supply at main circuit panel before installing. Do not connect electricity supply until your lamp is fully assembled and installed.
2. All wires are connected. Do not remove the lamp from its packaging by pulling on the power cord, as a bad connection may result.
3. To reduce the risk of fire, electrical shock, or personal injury, always turn off the lamp and allow it to cool prior to replacing light bulb. Do not touch bulb when fixture is turned on or look directly at light bulb. Keep flammable materials away from light bulb.
4. Deviation from instructions may result in a risk of fire or electric shock.

### PRODUCT DESCRIPTION:

General material: Iron  
 Height: 80.0cm (30.5in)  
 Length: 80.0cm (30.5in)  
 Width: 8.9cm (3.5in)  
 Weight: 41.8kg (92.15lbs)  
 Grounded / Hardwired

### ASSEMBLY INSTRUCTIONS:

1. Carefully remove all parts from the box and remove all plastic covering.
2. Turn OFF power to the junction box where the wall light will be installed.
3. Attach the wall mounting plate (D) to the wall with mounting screws (B).
4. For US Market: Connect the ground wire from the fixture to the ground (Usually the green or bare wire) with a plastic wire nut (C1) and wrap the connection with electrical tape. Connect the hot wire to the hot junction box wire (Usually black or smooth) with a plastic wire nut (C1) and wrap the connection with electrical tape. Connect the neutral wire to the neutral junction box wire (Usually white or ribbed) with a plastic wire nut (C1) and wrap the connection with electrical tape.
5. For non-US Market: Connect the wire from the fixture into the terminal block (C2), ensure the wires correspond to the labelled terminal. The incoming Live supply should be connected into the terminal marked "L"; The incoming NEUTRAL supply should be connected into the terminal marked "N". If you have one or more than one incoming Earth wire, connect it or them together into the terminal marked with the Earth Logo.
6. Attach the steel cable from fixture to the hook of the wall mounting plate (D) with quick link, then hang the body (E) onto the wall mounting plate (D).
7. Restore power to junction box and test wall light fixture.

### CARE INSTRUCTIONS:

1. Make sure that the power is turned off and bulb has cooled before handling.
2. Wipe clean with a dry cloth. Do not use corrosive cleaners.
3. The cable/cord of this wall lamp cannot be replaced: if the cable is damaged, do not use the lamp.

### ENVIRONMENT:

Special waste handling may be required. Please contact your local authorities for more information.

